

VIEW™ | Constant Voltage Transformer

XT9170 - Transformer

ClearOne's Constant Voltage Transformer allows VIEW Amplifiers to be used with 70V or 100V speaker systems.

ClearOne®



CONSTANT
VOLTAGE
TRANSFORMER

APPLICATIONS

- + Conferencing
- + Multi-zone Paging
- + Emergency Communications
- + Business Entertainment
- + Sound Reinforcement

ADVANTAGES

- + Converts 8 ohm signal to 70 or 100 volt current.
- + Can be installed in a rack or freestanding.
- + The XT9170 accepts 8 ohm input using a 2-pin phoenix connector and outputs at 70/100 Volts. This allows the transformer to be used standalone, or with ClearOne VIEW, allowing for a bridge between the IP A/V system and a conventional approach with 70v/100v speakers.

> VIEW REAR PANEL



> Speakers per XT9170 Zone / Transformer Tap Settings

Note - The chart shows how many 70v/100v speakers can be supported per zone with the respective 70v/100v tap settings.

Part Number XT9170

Speakers per Zone based on Speaker Tap Values								
Amplifier	Channels	RMS Wattage	1/2 W	1 W	2 W	4 W	8 W	16 W
SL254	2	25	50	25	12	6	3	1
SL251	2	50	100	50	25	12	6	3
SL9250	2	50	100	50	25	12	6	3
AMP2200	2	200	400	200	100	50	25	12
AMP2200 Bridged	2	600	1200	600	300	150	75	13

Powered by StreamNet™

> CLEARONE LOCATIONS

Headquarters:
Salt Lake City, UT USA
5225 Wiley Post Way
Suite 500
Salt Lake City, UT 84116
Tel: 801-975-7200
Toll Free: 800-945-7730
Fax: 801-977-0087
sales@clearone.com

Latin America
Tel: 801-974-3621
global@clearone.com

EMEA
Tel: 44 (0) 1189 036 053
global@clearone.com

APAC
Tel: 801-303-3388
global@clearone.com