

# DIMIC12S

DIMIC12 EXTENSION



## EXPANDABLE UP TO 64 ZONES

DIMIC12S is an extension unit for the DIMIC12 digital paging station. Per DIMIC12 you can connect up to 7 DIMIC12S expansion units allowing a total of 96 programmable buttons available.

When the DIMIC12(S) is used with AUDIOCONTROL12.8 you can allocate buttons to perform actions like opening a door, controlling a sound source, ring a bell or even start a series of commands.

DIMIC12S is a selective programmable digital paging station extension unit of DIMIC12 for use with AUDIOCONTROL12.8 that is easy to configure via the host's graphical user interface.

- For use with DIMIC12 and AUDIOCONTROL12.8
- Inconspicuous and elegant design
- Remarkable sound quality
- Push-to-talk button and multicolor paging status LED
- 12 selection buttons and status LED's
- Universal configuration of push buttons
- Expandable up to 64 zones or presets
- Virtually endless applications
- Wall mounting possibilities

## TECHNICAL SPECIFICATIONS

<b>Dimensions base (w x d x h)</b>	110 x 240 x 58 mm
<b>Cut-out dimensions</b>	85 x 230 mm
<b>Weight</b>	350 g
<b>Power supply</b>	12 - 24 VDC/75 mA max
<b>Accessories</b>	Mounting brackets, link cable, manual, CAT5 cable 5m