VC3102

AUDAC

Features

- Flexible system
- 100 Watt power rating
- 11 steps of 3dB
- Built in relay for priority signals
- Slim design
- Blends beautifully into walls
- Easy installation

Applications

- Private houses
- Industrial buildings
- Offices
- ...



The VC3102 is a 100 Volt volume controller which can handle a power of up to 100 Watt.

The volume is adjustable with a rotatable knob in 11 steps of 3dB.

It is equipped with a relay and separate input for the reception of 24V priority signals. This means that when a priority signal occurs, the volume will be automatically switched to maximum level.

This can be very useful for emergency and evacuation messages.

Due to it's slim and good looking design, these volume controls will blend into all kinds of different environments or interiors.

The construction is made of sturdy ABS and therefore suitable for big projects in industrial buildings as well as standard home interiors.

The dimensions are 80 mm x 80 mm, and a built-in depth of 46 cm is required.

The connections are made at the back with screw clamp connectors.

▶ Specifications

SYSTEM SPECIFICATIONS	
Max handling power	100 W
Max. operation voltage	100 V
Attenuation	11 x 3 dB
Relay	24 V - 25 mA
Priority Input	24V DC
PRODUCT FEATURES	
Dimensions (Width x Height x Depth)	80 x 80 x 50 mm
Built-in Depth	46 mm
Weight net	340 g
Construction	ABS
Colour	White
SHIPPING & ORDERING	
Packaging	Carton box
Shipping weight & volume	370 g - 0.0008Cbm

^{*}AUDAC reserves the right to change specifications without notice: this is part of our policy to continually improve our product